

BRC - Installation Instructions

Models BRC-XX



Bbasics
by luminii

7777 Merrimac Ave
Niles, IL 60714
T 224.333.6033
F 224.757.7557
info@luminii.com
www.luminii.com

REVO.1
02222024

1 / 2

Please read all instructions prior to installation and keep for future reference!

1. PRODUCT TO BE INSTALLED BY A QUALIFIED ELECTRICIAN.
2. USE ONLY WITH CLASS 2 POWER UNIT.
3. 24 VOLTS DC.
4. SUITABLE FOR DAMP LOCATIONS.
5. RECESSED MOUNT
6. SUITABLE FOR INSTALLATION WITHIN THE CLOSET STORAGE SPACE.
7. INHERENTLY PROTECTED

1

Caution: Safety equipment is recommended, when modifications are being made to the extrusion & lens.

1.1 If necessary extrusion & lens can be cut in the field. Using the proper blade for aluminum, cut to the desired length.

2

2.1 LineLED can be shortened by cutting along the dashed lines in between the solder pads. Make sure the cut is made on the side of the LineLED without the wire leads. LineLED cannot touch the metal endcap which will shorten the circuit

3

3.1 Install endcaps at each ends of the extrusion.

4

4.1 Insert extrusion into opening, use screw to secure .

4.2 Screws should be spaced every 14" for proper securement.

5

5.1 Prior to installing LineLED to extrusion, clean extrusion from any debris. Make sure powerfeed go through powerfeed opening on end cap first. Then gently push LineLED onto aluminum extrusion.

BRC - Installation Instructions

Models BRC-XX

Please read all instructions prior to installation and keep for future reference!

1. PRODUCT TO BE INSTALLED BY A QUALIFIED ELECTRICIAN.
2. USE ONLY WITH CLASS 2 POWER UNIT.
3. 24 VOLTS DC.
4. SUITABLE FOR DAMP LOCATIONS.
5. RECESSED MOUNT
6. SUITABLE FOR INSTALLATION WITHIN THE CLOSET STORAGE SPACE.
7. INHERENTLY PROTECTED



REVO.1
02222024

2 / 2

Bbasics
by luminii

7777 Merrimac Ave
Niles, IL 60714
T 224.333.6033
F 224.757.7557
info@luminii.com
www.luminii.com

